

A View Towards **Excellence**

1-888-949-3667

Wizard Screens

4263 Phillips Avenue **Burnaby BC** V5A 2X4

Programing Remote - Tips & Tricks Adjusting the Limits

Adjusting the Top Limit

- 1. Send the unit to the top limit by pressing the UP button
- 2. Once at the top limit
 - a. Press & HOLD the Up & DOWN buttons until the unit jogs up & down once
 - b. Then press the UP or DOWN buttons to set the top limit where you want
 - c. Once you have it at the right spot press & hold the MY button unit the screen jogs up & down
 - d. The new top limit is now set

Adjusting the lower limit

- 1. Send the unit to the lower limit by pressing the DOWN button
- 2. Once at the lower limit
 - a. Press & HOLD the Up & DOWN buttons until the unit jogs up & down once
 - b. Then press the UP or DOWN buttons to set the lower limit where you want
 - c. Once you have it at the right spot press & hold the MY button unit the screen jogs up & down
 - d. The new lower limit is now set

Adding/Removing Units to a Channel

Add Unit to a Channel (Copy & Paste) – Used Most Often When Adding All Units to One Channel (All Channel)

- 1. Select the current channel the unit is on
- 2. Once on the channel press & hold the PROGRAM button until the screen jogs up & down once (copy)
- 3. Select the channel you want to add the unit to
- 4. Once on that channel press & hold the PROGRAM button until the screen jogs up & down once (paste)
- 5. Repeat the steps on every channel you want to copy to a new channel

*ATTENTION: If you paste a unit on to a channel where that unit is already on then the unit will be deleted from that channel & you will need to do a Full Power Reset to add that unit to that remote

What if 1 channel has too many units on it (more than one) & you want to remove one (or more) of the units from that channel?

- 1. Select the channel all the units are on
- 2. Copy that channel by pressing & holding the PROGRAM button until the screen jogs up & down
- 3. Move to another channel & Paste those units on to that channel by pressing & holing the PROGRAM button until the screens jog up & down
- 4. Once all the screens are on both channels, unplug the unit that you want on the original channel
- 5. Then copy the 2nd channel with only the one screen plugged in by pressing & holding the PROGRAM button unit the screen jogs up & down
- 6. Then paste that unit on to the first channel by pressing & holding the PROGRAM button until the screen jogs up & down
- 7. That unit is not deleted from that channel & you can plus the other unit in
- 8. Test both channels











A View Towards **Excellence**

1-888-949-3667

Wizard Screens

4263 Phillips Avenue Burnaby BC V5A 2X4

- 9. If the 2nd channel still has both units, then copy the first channel with the one unit on it
- 10. Once it's copied paste it on to the 2nd channel
- 11. That will delete it from the 2nd channel & each channel will have one unit on it
- 12. Repeat as necessary

Adjusting the Obstacle Detection Sensitivity

Please see the below video for adjusting the obstacle detection sensitivity www.youtube.com/watch?v=SyI550rLCMk&t=6s







